



GFP Polytrans Transformers

- UL 2161 Type 4
- Self-Contained
- Does Not Require an Additional Transformer Box and Disconnect Switch
- Epoxy Resin Fill
- Service Bypass Switch
- Tri-LED Sensor Lamp Indicator
- 30 and 60 mA, 60 Hertz
- 120 V. and 277 V.

- Ground - Does not require a dedicated ground wire connected to the service panel. An LED will indicate when a proper ground is detected.
- Neutral Line Voltage - No tripping when there is excessive white wire voltage.
- Bypass Button - An easy way to check and service secondary ground faults
- Polarity - Will operate when black and white wires are reversed. An LED will indicate polarity is incorrect.
- Mid Point Return - All wiring methods are approved.
- The best choice for remote wired sign installations.
- Perfect for servicing Pre-UL2161 signs.

NORMAL POWER FACTOR - 120 V.

CATALOG NO.	VOLTS	mA	WATTS	INPUT AMP	LENGTH	WIDTH	HEIGHT	MOUNTING	N. WT (LBS.)	Footprint Drawing
PNT1512N3G	15,000	30	243	3.71	10-3/4"	4-1/4"	7"	11-3/4" X 2"	24	View Drawing
PNT1212N3G	12,000	30	194	2.80	10-3/4"	4-1/4"	7"	11-3/4" X 2"	23	View Drawing
PNT912N3G	9,000	30	146	2.16	10-3/4"	3-5/8"	6-1/4"	11-3/4" X 2"	15	View Drawing
PNT712N3G	7,500	30	122	1.70	10-3/4"	3-5/8"	6-1/4"	11-3/4" X 2"	14	View Drawing
PNT612N3G	6,000	30	97	1.34	10-3/4"	3-5/8"	6-1/4"	11-3/4" X 2"	14	View Drawing
PNT512N3G	5,000	30	80	1.20	10-3/4"	3-5/8"	6-1/4"	11-3/4" X 2"	14	View Drawing
PNT412N3G	4,000	30	65	0.87	10-3/4"	3-5/8"	6-1/4"	11-3/4" X 2"	14	View Drawing
PNT1512N6G	15,000	60	486	7.50	12-1/16"	4-15/16"	7-11/16"	13-1/4" X 2-3/4"	46	View Drawing
PNT1212N6G	12,000	60	389	6.00	10-5/16"	4-15/16"	6-13/16"	11-1/2" X 2-3/4"	29	View Drawing
PNT912N6G	9,000	60	292	4.50	10-13/16"	4-5/16"	7-3/16"	11-7/8" X 2"	25	View Drawing
PNT712N6G	7,500	60	243	3.75	10-13/16"	4-5/16"	7-3/16"	11-7/8" X 2"	24	View Drawing
PNT612N6G	6,000	60	194	3.00	10-13/16"	4-5/16"	7-3/16"	11-7/8" X 2"	23	View Drawing

PNT512N6G	5,000	60	162	2.50	10-13/16"	3-3/4"	6-3/8"	11-7/8" X 2"	17	View Drawing
PNT412N6G	4,000	60	130	2.00	10-13/16"	3-3/4"	6-3/8"	11-7/8" X 2"	15	View Drawing
PNT312N6G	3,000	60	97	1.50	10-13/16"	3-3/4"	6-3/8"	11-7/8" X 2"	15	View Drawing

NORMAL POWER FACTOR - 277 V.

CATALOG NO.	VOLTS	mA	WATTS	INPUT AMP	LENGTH	WIDTH	HEIGHT	MOUNTING	N. WT (LBS.)	Footprint Drawing
PNT1527N3G	15,000	30	243	1.59	10-3/4"	4-1/4"	7"	11-3/4" X 2"	24	View Drawing
PNT1227N3G	12,000	30	194	1.14	10-3/4"	4-1/4"	7"	11-3/4" X 2"	23	View Drawing
PNT927N3G	9,000	30	146	0.86	10-3/4"	3-5/8"	6-1/4"	11-3/4" X 2"	15	View Drawing
PNT727N3G	7,500	30	122	0.79	10-3/4"	3-5/8"	6-1/4"	11-3/4" X 2"	14	View Drawing
PNT627N3G	6,000	30	97	0.57	10-3/4"	3-5/8"	6-1/4"	11-3/4" X 2"	14	View Drawing
PNT527N3G	5,000	30	80	0.49	10-3/4"	3-5/8"	6-1/4"	11-3/4" X 2"	14	View Drawing
PNT427N3G	4,000	30	65	0.38	10-3/4"	3-5/8"	6-1/4"	11-3/4" X 2"	14	View Drawing
PNT1527N6G	15,000	60	486	3.25	12-1/16"	4-15/16"	7-11/16"	13-1/4" X 2-3/4"	46	View Drawing
PNT1227N6G	12,000	60	389	2.60	10-5/16"	4-15/16"	6-13/16"	11-1/2" X 2-3/4"	29	View Drawing
PNT927N6G	9,000	60	292	1.95	10-13/16"	4-5/16"	7-3/16"	11-7/8" X 2"	25	View Drawing
PNT727N6G	7,500	60	243	1.63	10-13/16"	4-5/16"	7-3/16"	11-7/8" X 2"	24	View Drawing
PNT627N6G	6,000	60	194	1.30	10-13/16"	4-5/16"	7-3/16"	11-7/8" X 2"	23	View Drawing
PNT527N6G	5,000	60	162	1.10	10-13/16"	3-3/4"	6-3/8"	11-7/8" X 2"	17	View Drawing
PNT427N6G	4,000	60	130	0.87	10-13/16"	3-3/4"	6-3/8"	11-7/8" X 2"	15	View Drawing
PNT327N6G	3,000	60	97	0.65	10-13/16"	3-3/4"	6-3/8"	11-7/8" X 2"	15	View Drawing